



Application Note 102

Avoiding Bus Contention on Configuration

KS8993, KS8995E, KS8997, KS8999

General Description

When programming configuration pins with an FPGA, the following recommendations can minimize bus contention.

These recommendations apply to the KS8993, KS8995E, KS8997, and KS8999, but are referred to as KS899x in this application note.

Scenario

A reset is applied to the KS899x. Shortly after the reset is de-asserted, the KS899x latches strap-in values on the configuration pins as shown in Figure 1.




Figure 1. KS899x Strap-In Window

Then the KS899x begins normal operation and may begin driving the configuration pins.

Recommendations

There is a possibility of contention if an FPGA is used to drive these pins and its outputs are not tri-stated before the KS899x begins driving signals on the configuration pins.

To ensure proper strap-in and minimize any contention on the configuration pins, an FPGA driving these signals should remain on after the active low reset signal is de-asserted for the duration of the strap-in window, and then be tri-stated immediately.

The recommended strap-in window is given in Table 1.

Part Number	t _{strap}
KS8993	30μs
KS8995E	50μs
KS8997	50μs
KS8999	50μs

Table 1. Recommended Strap-In Window

Also recommended is a series resistor between the FPGA output and the KS899x's configuration pin as shown in Figure 2. This helps to limit the current if some contention should still occur due to the limited control of the FPGA outputs. For example, a resistor value of 250Ω would limit a TTL logic high of 2.5V to 10mA.




Figure 2. KS899x Current Limiting Resistor

Please contact your local Micrel FAE or salesperson if you have any questions.

MICREL, INC. 1849 FORTUNE DRIVE SAN JOSE, CA 95131 USA

TEL + 1 (408) 944-0800 FAX + 1 (408) 944-0970 WEB <http://www.micrel.com>

The information furnished by Micrel in this data sheet is believed to be accurate and reliable. However, no responsibility is assumed by Micrel for its use. Micrel reserves the right to change circuitry and specifications at any time without notification to the customer.

Micrel Products are not designed or authorized for use as components in life support appliances, devices or systems where malfunction of a product can reasonably be expected to result in personal injury. Life support devices or systems are devices or systems that (a) are intended for surgical implant into the body or (b) support or sustain life, and whose failure to perform can be reasonably expected to result in a significant injury to the user. A Purchaser's use or sale of Micrel Products for use in life support appliances, devices or systems is at Purchaser's own risk and Purchaser agrees to fully indemnify Micrel for any damages resulting from such use or sale.

© 2004 Micrel, Incorporated